Cambridge Assessment International Education

Cambridge International AS & A Level

CANDIDATE NAME

CENTRE NUMBER

CANDIDATE NUMBER

CS BY AQIB KHAN

8172456601

COMPUTER SCIENCE **9618/12**

Paper 1 Theory Fundamentals **October/November 2024**

1 hour 30 minutes

You must answer on the question paper.

No additional materials are needed.

INSTRUCTIONS

- Answer **all** questions.
- Use a black or dark blue pen.
- Write your name, centre number and candidate number in the boxes at the top of the page.
- Write your answer to each question in the space provided.
- Do **not** use an erasable pen or correction fluid.
- Do **not** write on any bar codes.
- You may use an HB pencil for any diagrams, graphs or rough working.
- Calculators must **not** be used in this paper.

INFORMATION

- The total mark for this paper is 75.
- The number of marks for each question or part question is shown in brackets [ ].
- No marks will be awarded for using brand names of software packages or hardware.

THE AQIB KHAN
AN INSTITUTE OF O/A LEVEL

This document has **16** pages. Any blank pages are indicated.

DC (WW/CB) 337421/2

© UCLES 2024

[Turn over

TAK (The AQIB KHAN)- An institute of O/A level

Aki Khan CS By AQIB Khan CS By AQIB KHAN TheAkikhan.com +92 3145030717

https://xtremepape.rs/

1 **(a)** Complete the truth table for the logic expression:

X = (**A** XOR **B**) NAND (**A** AND (**B** XOR **C**))

A	B	C	Working space	X
0	0	0		
0	0	1		
0	1	0		
0	1	1		
1	0	0		
1	0	1		
1	1	0		
1	1	1		

[2]

(b) Draw the logic circuit for the logic expression:

W = **P** NAND ((**Q** OR NOT **R**) XOR (**P** XOR **Q**))



[2]

THE AQIB KHAN
AN INSTITUTE OF O/A LEVEL

DO NOT WRITE IN THIS MARGIN
DO NOT WRITE IN THIS MARGIN
DO NOT WRITE IN THIS MARGIN
DO NOT WRITE IN THIS MARGIN
DO NOT WRITE IN THIS MARGIN

CS BY AQIB KHAN

https://xtremepape.rs/

DO NOT WRITE IN THIS MARGIN
DO NOT WRITE IN THIS MARGIN
DO NOT WRITE IN THIS MARGIN
DO NOT WRITE IN THIS MARGIN
DO NOT WRITE IN THIS MARGIN

2 Embedded systems are used in many electronic devices.

(a) Describe the drawbacks of embedded systems.

.....

.....

.....

.....

.....

..... [3]

(b) An embedded system has Dynamic RAM (DRAM).

Identify **one** benefit of using DRAM instead of Static RAM (SRAM) in an embedded system.

.....

..... [1]

(c) Give **two** differences between Erasable Programmable ROM (EPROM) and Electrically Erasable Programmable ROM (EEPROM).

Difference 1 .....

.....

.....

Difference 2 .....

.....

..... [2]

CS BY AQIB KHAN
THE AQIB KHAN
AN INSTITUTE OF O/A LEVEL

TAK (The AQIB KHAN) An institute of O/A level
Aki Khan CS By AQIB Khan CS By AQIB KHAN TheAkikhan.com +92 3145030717
https://xtremepape.rs/

3 A student has a computer.

(a) The computer is designed using the Von Neumann model for a computer system.

Complete the table by describing the purpose of each of the given registers.

Register	Purpose
Program Counter (PC)	....
Memory Address Register (MAR)	....
Memory Data Register (MDR)	....
Index Register (IX)	....

[4]

DO NOT WRITE IN THIS MARGIN
DO NOT WRITE IN THIS MARGIN
DO NOT WRITE IN THIS MARGIN
DO NOT WRITE IN THIS MARGIN
DO NOT WRITE IN THIS MARGIN
CS BY AQIB KHAN
THE AQIB KHAN
AN INSTITUTE OF O/A LEVEL

DO NOT WRITE IN THIS MARGIN
DO NOT WRITE IN THIS MARGIN
DO NOT WRITE IN THIS MARGIN
DO NOT WRITE IN THIS MARGIN
DO NOT WRITE IN THIS MARGIN

CS BY AQIB KHAN

(b) The student needs to connect the computer to a monitor that has a screen resolution of 2560 × 1600 pixels. The monitor also has built-in speakers.

The computer has a Video Graphics Array (VGA) port and a High Definition Multimedia Interface (HDMI) port.

Explain the benefits of connecting the monitor to the computer using the HDMI port instead of the VGA port.

.....

.....

.....

.....

.....

.....

.....

..... [4]

(c) The computer has an Operating System (OS). One of the key management tasks of the OS is process management.

Describe the process management tasks performed by an OS.

.....

.....

.....

.....

.....

.....

.....

..... [4]

THE AQIB KHAN
AN INSTITUTE OF O/A LEVEL

TAK (The AQIB KHAN) An institute of O/A level
Aki Khan CS By AQIB Khan CS By AQIB KHAN TheAkikhan.com +92 3145030717
https://xtremepape.rs/

4 A program is written in a high-level language by a team of three programmers using an Integrated Development Environment (IDE).

(a) Describe how the programmers can use the debugging features of a typical IDE during the development of the program.

.....

.....

.....

.....

.....

.....

.....

..... [4]

(b) The programmers created a new program library whilst developing the program.

Describe the benefits to the programmers of creating a program library.

.....

.....

.....

.....

.....

..... [3]

(c) The file containing the final program code will be sent by email for beta testing.

Identify **one** security method that can be used to protect the program code from unauthorised access during email transfer.

Explain how your chosen method protects the program code.

Security method .....

.....

Explanation .....

.....

.....

..... [3]

DO NOT WRITE IN THIS MARGIN
DO NOT WRITE IN THIS MARGIN
DO NOT WRITE IN THIS MARGIN
DO NOT WRITE IN THIS MARGIN
DO NOT WRITE IN THIS MARGIN
CS BY AQIB KHAN
THE AQIB KHAN INSTITUTE OF O/A LEVEL

https://xtremepape.rs/

DO NOT WRITE IN THIS MARGIN
DO NOT WRITE IN THIS MARGIN
DO NOT WRITE IN THIS MARGIN
DO NOT WRITE IN THIS MARGIN
DO NOT WRITE IN THIS MARGIN

5 A computer programmer is learning about the importance of acting ethically at work.

(a) Explain the reasons why the computer programmer needs to act ethically towards colleagues and the public.

Colleagues .....

.....

.....

.....

The public .....

.....

.....

.....

[4]

(b) The programmer writes a program to be used in a business. The source code of the program can be modified by the business. The business pays the programmer for the maintenance and security updates.

(i) Identify **one** suitable type of software licence for the program **and** describe the reasons for your choice.

Type of software licence .....

Reasons for choice .....

.....

.....

.....

[3]

(ii) Explain the reasons why the programmer should copyright their program.

.....

.....

.....

..... [2]

CS BY AQIB KHAN
THE AQIB KHAN
AN INSTITUTE OF O/A LEVEL

TAK (The AQIB KHAN) An institute of O/A level
Aki Khan CS By AQIB Khan CS By AQIB KHAN TheAkikhan.com +92 3145030717
https://xtremepape.rs/

6 A company uses a relational database to store data about its customers, employees and the individual repair jobs that customers have booked.

(a) Explain the benefits of using a relational database instead of a file-based approach.

.....

.....

.....

.....

.....

..... [3]

(b) The company decides which employees will work on each repair job. An employee can log into the database to access information about their repair jobs.

The database is normalised and includes these tables:

- `CUSTOMER` stores personal data about each customer
- `EMPLOYEE` stores personal data about each employee
- `LOGIN_DATA` stores the username and password for each employee
- `JOB` stores the data about each repair job
- `JOB_EMPLOYEE` stores the employees that are working on each repair job.

(i) Identify each relationship between the database tables **and** explain how each relationship can be implemented in the normalised database.

.....

.....

.....

.....

.....

.....

.....

.....

.....

.....

.....

..... [6]

DO NOT WRITE IN THIS MARGIN
DO NOT WRITE IN THIS MARGIN
DO NOT WRITE IN THIS MARGIN
DO NOT WRITE IN THIS MARGIN
DO NOT WRITE IN THIS MARGIN
CS BY AQIB KHAN
THE AQIB KHAN
AN INSTITUTE OF O/A LEVEL

DO NOT WRITE IN THIS MARGIN
DO NOT WRITE IN THIS MARGIN
DO NOT WRITE IN THIS MARGIN
DO NOT WRITE IN THIS MARGIN
DO NOT WRITE IN THIS MARGIN

CS BY AQIB KHAN

(ii) The database also has the table `INVOICE` that stores data about each invoice that is sent to a customer.

Example data from the table `INVOICE` is given.

InvoiceID	DateSent	Amount	Paid	JobID
29262	12/12/2023	105.20	Y	221
26765	11/11/2023	200.00	Y	315
13290	02/01/2024	50.00	Y	315
34090	05/02/2024	25.95	N	569

Write a Structured Query Language (SQL) script to return the total amount of all the invoices sent in the year 2023 that have been paid.

.....

.....

.....

.....

.....

..... [3]

THE AQIB KHAN
AN INSTITUTE OF O/A LEVEL

TAK (The AQIB KHAN) An institute of O/A level
Aki Khan CS By AQIB Khan CS By AQIB KHAN TheAkikhan.com +92 3145030717
https://xtremepape.rs/

7 A student takes a photograph of a science experiment.

(a) The photograph is saved as a bitmapped image.

(i) Define the following bitmap terms.

Colour depth .....

.....

File header .....

.....

[2]

(ii) Explain why changing the image resolution will affect the image quality and file size.

Image quality .....

.....

.....

File size .....

.....

.....

[2]

(iii) Identify **one** lossless method of compressing an image.

..... [1]

(b) The student draws a picture on paper that is scanned into the computer and saved as a vector graphic.

Define the vector graphic terms property and drawing list.

Property .....

.....

Drawing list .....

.....

[2]

DO NOT WRITE IN THIS MARGIN
DO NOT WRITE IN THIS MARGIN
DO NOT WRITE IN THIS MARGIN
DO NOT WRITE IN THIS MARGIN
DO NOT WRITE IN THIS MARGIN
CS BY AQIB KHAN
THE AQIB KHAN
AN INSTITUTE OF O/A LEVEL

BLANK PAGE

DO NOT WRITE IN THIS MARGIN
DO NOT WRITE IN THIS MARGIN
DO NOT WRITE IN THIS MARGIN
DO NOT WRITE IN THIS MARGIN
DO NOT WRITE IN THIS MARGIN
CS BY AQIB KHAN
THE AQIB KHAN
AN INSTITUTE OF O/A LEVEL

https://xtremepape.rs/

8 The following table shows part of the instruction set for a processor. The processor has two registers, the Accumulator (ACC) and the Index Register (IX).

Instruction		Explanation
Opcode	**Operand**	
LDM	#n	Immediate addressing. Load the number n to ACC
LDD	<address>	Direct addressing. Load the contents of the location at the given address to ACC
LDI	<address>	Indirect addressing. The address to be used is at the given address. Load the contents of this second address to ACC
LDX	<address>	Indexed addressing. Form the address from <address> + the contents of the index register. Copy the contents of this calculated address to ACC
LDR	#n	Immediate addressing. Load the number n to IX
ADD	#n/Bn/&n	Add the number n to the ACC
ADD	<address>	Add the contents of the given address to the ACC
SUB	#n/Bn/&n	Subtract the number n from the ACC
SUB	<address>	Subtract the contents of the given address from the ACC
INC	<register>	Add 1 to the contents of the register (ACC or IX)
DEC	<register>	Subtract 1 from the contents of the register (ACC or IX)

<address> can be an absolute or a symbolic address
# denotes a denary number, e.g. #123
B denotes a binary number, e.g. B01001010
& denotes a hexadecimal number, e.g. &4A

THE AQIB KHAN
AN INSTITUTE OF O/A LEVEL
CS BY AQIB KHAN
DO NOT WRITE IN THIS MARGIN
DO NOT WRITE IN THIS MARGIN
DO NOT WRITE IN THIS MARGIN
DO NOT WRITE IN THIS MARGIN
DO NOT WRITE IN THIS MARGIN

https://xtremepape.rs/

DO NOT WRITE IN THIS MARGIN
DO NOT WRITE IN THIS MARGIN
DO NOT WRITE IN THIS MARGIN
DO NOT WRITE IN THIS MARGIN
DO NOT WRITE IN THIS MARGIN

CS BY AQIB KHAN

(a) The current contents of memory are shown:

Address	Data
19	25
20	23
21	2
22	4
23	15
24	50
25	22

The current contents of the ACC and IX are shown:

ACC	50
IX	20

Complete the table by writing the content of the ACC and the IX after each set of instructions has run.

	Instructions	ACC content	IX content
1	`LDM #19` `DEC ACC`		
2	`LDD 23` `ADD 19`		
3	`LDI 25` `INC ACC`		
4	`LDR #21` `LDX 2`		

[5]

THE AQIB KHAN
AN INSTITUTE OF O/A LEVEL

TAK (The AQIB KHAN) An institute of O/A level
Aki Khan CS By AQIB Khan CS By AQIB KHAN TheAkikhan.com +92 3145030717
https://xtremepape.rs/

(b) The instruction set also includes these bit manipulation instructions:

Instruction		Explanation
Opcode	**Operand**	
AND	#n/Bn/&n	Bitwise AND operation of the contents of ACC with the operand
AND	<address>	Bitwise AND operation of the contents of ACC with the contents of <address>
XOR	#n/Bn/&n	Bitwise XOR operation of the contents of ACC with the operand
XOR	<address>	Bitwise XOR operation of the contents of ACC with the contents of <address>
OR	#n/Bn/&n	Bitwise OR operation of the contents of ACC with the operand
OR	<address>	Bitwise OR operation of the contents of ACC with the contents of <address>
LSL	#n	Bits in ACC are shifted logically n places to the left. Zeros are introduced on the right-hand end
LSR	#n	Bits in ACC are shifted logically n places to the right. Zeros are introduced on the left-hand end.
<address> can be an absolute or a symbolic address # denotes a denary number, e.g. #123 B denotes a binary number, e.g. B01001010 & denotes a hexadecimal number, e.g. &4A		

The current content of the ACC is shown:

ACC	1	0	0	1	1	0	1	0

(i) The table has three sets of instructions. The binary number 10011010 is reloaded into the ACC before each set of instructions is run.

Complete the table by writing the content of the ACC after each set of instructions has run.

	Instructions	ACC content
1	LSL #2	
2	ADD #5 AND #30	
3	OR B11110010 INC ACC	

[3]

DO NOT WRITE IN THIS MARGIN
DO NOT WRITE IN THIS MARGIN
DO NOT WRITE IN THIS MARGIN
DO NOT WRITE IN THIS MARGIN
DO NOT WRITE IN THIS MARGIN
CS BY AQIB KHAN

https://xtremepape.rs/

DO NOT WRITE IN THIS MARGIN
DO NOT WRITE IN THIS MARGIN
DO NOT WRITE IN THIS MARGIN
DO NOT WRITE IN THIS MARGIN
DO NOT WRITE IN THIS MARGIN

(ii) Explain how bit manipulation can be used to test whether the binary number stored in the ACC represents an odd denary number.

Write the bit manipulation instruction that will be used.

Explanation .....

.....

.....

.....

.....

Instruction .....

[3]

CS BY AQIB KHAN
THE AQIB KHAN
AN INSTITUTE OF O/A LEVEL

https://xtremepape.rs/

9 A road bridge has a weight limit and a height limit for vehicles. For example, a vehicle must weigh less than 10 000 kg and must have a height of less than 3 m.

The bridge has a warning system. If a vehicle is approaching the bridge and it exceeds one or both limits, a sign displays a warning telling the driver of the vehicle to stop.

(a) The bridge warning system uses sensors to detect if a vehicle exceeds the limits.

Complete the table by identifying **two** different sensors that could be used by the system **and** describe how each sensor is used by the system.

Sensor	Use in bridge warning system
.....	.....
.....	.....
	.....
.....	.....
.....	.....
	.....

[2]

(b) Explain whether the bridge warning system is an example of a monitoring system or of a control system.

.....

.....

.....

..... [2]

THE AQIB KHAN
AN INSTITUTE OF O/A LEVEL

Permission to reproduce items where third-party owned material protected by copyright is included has been sought and cleared where possible. Every reasonable effort has been made by the publisher (UCLES) to trace copyright holders, but if any items requiring clearance have unwittingly been included, the publisher will be pleased to make amends at the earliest possible opportunity.

To avoid the issue of disclosure of answer-related information to candidates, all copyright acknowledgements are reproduced online in the Cambridge Assessment International Education Copyright Acknowledgements Booklet. This is produced for each series of examinations and is freely available to download at www.cambridgeinternational.org after the live examination series.

Cambridge Assessment International Education is part of Cambridge Assessment. Cambridge Assessment is the brand name of the University of Cambridge Local Examinations Syndicate (UCLES), which is a department of the University of Cambridge.

© UCLES 2024 9708/12/M/J/24

TAK (The AQIB KHAN) An institute of O/A level
Aki Khan CS By AQIB Khan CS By AQIB KHAN TheAkikhan.com +92 3145030717
https://xtremepape.rs/

DO NOT WRITE IN THIS MARGIN
DO NOT WRITE IN THIS MARGIN
DO NOT WRITE IN THIS MARGIN
DO NOT WRITE IN THIS MARGIN
DO NOT WRITE IN THIS MARGIN
CS BY AQIB KHAN